


# DeKode

## iE 10S

### Quick User Guide



- 1/4" (6.35mm) TS mono input for plugging in your instrument.
- Power / Bluetooth Button  
Power On/Off: Press and hold the button.  
Bluetooth Control: When powered on, short press to turn on Bluetooth; double press to turn off Bluetooth.  
RGB LED Status Indicators:  
Flashing Blue: Bluetooth not connected / Pairing mode.  
Constant Blue Light: Bluetooth connected.  
Constant Red Light: Low battery.  
Flashing Red: Charging.  
PS: The status priority is Bluetooth > Battery > Preset.
- "+" / "-" Buttons: Press to adjust the Preset Volume; Press "+" and "-" simultaneously to Mute.
- Press the "◀" and "▶" buttons to switch between presets within the current bank (10 presets per bank, 5 banks total). Bank Switch Button "↔" Cycles through Preset Banks 1-5. When switching banks, the LED will flash for 3 seconds, then return to displaying the current preset status.  
Bank Color Coding: Green (Bank 1) → Cyan (Bank 2) → Yellow (Bank 3) → Purple (Bank 4) → White (Bank 5)
- USB Type-C Port Used for charging, connecting to a mobile phone or computer for recording, and firmware updates.
- 3.5mm (1/8") Stereo Output Jack Used for connecting headphones, active speakers, or other effects units.

### Specifications

#### Technical Specifications

A/D/A Converter: 24-bit  
Sampling Frequency: 44.1 kHz  
SNR:103dB  
Maximum Simultaneous Effects: 8  
Preset Memory: Built-in 50 factory presets

#### Analog Input Connections

IN: 1/4" (6.35mm) Unbalanced (TS), 1MΩ

#### Analog Output Connections

OUT (PHONES): 1/8" (3.5mm) Stereo (TRS), 100Ω

#### Digital Connections

USB Port: USB 2.0 Type-C Port

#### USB Recording Specification

Sample Rate: 44.1 kHz  
Bit Depth: 16-bit

#### Size and Weight

Dimensions: 84.3mm (w) x 43.7mm (D) x 32.2mm (H)  
Unit Weight: 64g

#### Power

Power Requirements: USB Type-C, DC 5V  
Built-in Lithium Battery: 1000mAh

#### FCC Caution:

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
  - Increase the separation between the equipment and receiver.
  - Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
  - Consult the dealer or an experienced radio/TV technician for help.
- The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.