



iG-10DMini

**ELECTRIC GUITAR AMPLIFIER  
WITH DRUM MACHINE**



**30**  
drum machine  
sound effects

**FCC Warning**

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:  
(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions,

may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on,

the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

NOTE 2: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

The device has been evaluated to meet general RF exposure requirement.

The device can be used in portable exposure condition without restriction.



MADE IN CHINA



中国制造

## Owner's Manual

# EN

In order to use this product properly and safely, please read this Owner's Manual carefully before using this product and keep it for future reference.

### iG-10D Mini

## Electric guitar amplifier with drum machine

### Product Specifications

Rated Power: 10W;  
Peak Power: 20W;  
Speaker Unit: Full-range 1.75 inch \* 5W \* 2;  
Charging: USB 5V 1000mA;  
Battery: 3.7V 2000mAh lithium battery;  
Instrument Input: 6.35mm interface;  
Signal-to-Noise Ratio: 80dB;  
Input Impedance: 1Mohm;  
Tone Frequency Range: 125-6.5KHz + 8dB  
Effects: Clean, Overdrive, Reverb,  
Drum Machine;  
AUX Input: 3.5mm interface;  
Signal-to-Noise Ratio: 95dB;  
Input Impedance: 10Kohm;

Bluetooth: V5.3 version  
(Bluetooth starts when powered on);  
Headphone Output: 3.5mm interface (stereo);  
Frequency Response: 40Hz-16KHz;  
Charging time: 2 hours;  
Battery life: 2-4 hours;  
Packaging dimensions:  
Length 160 \* Width 105 \* Height 110(mm);  
Net weight: 400g;  
Gross weight: 450g;

### Features



- (1). Guitar Input: For connecting guitar audio cable;
- (2). Power switch/Guitar volume: Rotate clockwise to 35 degrees to turn on, continue rotating to adjust guitar volume; rotate counterclockwise to 30 degrees to turn off;
- (3). Power/Charging indicator light: Stays on when powered on and fully charged, flashes when charging;
- (4). Mode switch: Lifted for clean tone, pressed for overdrive tone;
- (5). Gain knob: Adjusts the gain size of guitar input;
- (6). Tone knob: Adjusts guitar tone, clockwise enhances high frequencies, counterclockwise enhances low frequencies;
- (7). Drum machine switch (Bluetooth indicator light): Tap to turn on drum machine; tap three times to set tempo (drum machine adjusts rhythm speed based on the interval between taps), long press for 0.5 seconds to turn off drum machine;
- (8). Effect encoder: Default adjusts reverb size of guitar channel when powered on, tap to adjust drum machine volume (TAP lights up red), tap again to adjust drum kit rhythm (TAP lights up green), cycle repeats;
- (9). Accompaniment input: For connecting smartphones, computers, MP3, CD, etc., audio accompaniment; (this volume is not controlled by knob (2));
- (10). Headphone jack: Automatically disconnects speaker output when headphones are plugged in;
- (11). Charging input: Can connect to a 5V1A charger with a USB interface, charging indicator light (3) flashes when charging;

### Packaging Contents

1. One iG-10DMini speaker;
2. One USB to Type-C charging cable;
3. One product manual;